

EP-560A



Model Number	EP-560A
Max. Gas Production (L/h)	5600
Phase	3 ϕ 3W
Power requirement (AC)	220V 380V
Current	60A
Power (kW/hr)	14.3
Pressure(kg/cm ²)	1.5
Average water consumption (L/h)	3.3
Average coolant consumption (L/h)	3.4
Add water for generator	Auto
Reserve container (L)	15
Add coolant for generator	Auto
Reserve container (L)	50
Dimensions (mm)	700*1620*1400
Gros Weight (kg)	400
Space Requirement (mm)	500 (FRONT) 500(RIGHT& LEFT) 500(UP)&200(BACK)

■ Applications:

Incinerators, Steel Cutting, Foundry, Automobile Industry, Aluminum Industry, Petro-Chemical Industry, Boilers, Restaurants & Food Service Industry, Household Appliance and Air Conditioner Manufacturing, and more.

