

EP-168

(Single Burner)



Model Number	EP-168
Max. Gas Production(L/h)	680
Phase	Single
Power requirement (AC)	110V
Current	12A
Power (kW/h)	1-1.3
Pressure (kg/cm ²)	0.3
Average water consumption (L/h)	0.1
Average coolant consumption (L/h)	0.3
Add water for generator	Auto
Reserve container (L)	10
Add coolant for generator	Auto
Reserve container (L)	10
Dimensions (mm)	650*550*750
Gros Weight(kg)	60kg
Space Requirement (mm)	500(FRONT),800(UP) 0 (RIGHT&LEFT&BACK)

- Applications:cooking

EP-200

(Dual Burner)



Model Number	EP-200
Max. Gas Production(L/h)	1800
Phase	Single
Power requirement (AC)	220V
Current	10- 15A
Power (kW/h)	3.3
Pressure (kg/cm ²)	0.5
Average water consumption (L/h)	0.6
Average coolant consumption (L/h)	0.6
Add water for generator	Auto
Reserve container (L)	15
Add coolant for generator	Auto
Reserve container (L)	15
Dimensions (mm)	1100* 640* 930
Gros Weight(kg)	150kg
Space Requirement (mm)	500(FRONT),800(UP) 0 (RIGHT&LEFT&BACK)